



Owner's Manual

INPUT - connect to guitar or effect before Loop or Loop before Loop

OUTPUT - connect to amp or another Loop

1 or T SEND - connect to first pedal (in Loop 1) input, or Tuner input

1 RETURN - connect to last pedal (in Loop 1) output

2 SEND - connect to first pedal (in Loop 2) input

2 RETURN - connect to last pedal (in Loop 2) output

* Use the SmolскиTech Dual Loop anywhere to eliminate loading down of signal. For use where you experience loss of tone and/or volume while pedals are bypassed (or off). Loop 1 is wired in series with loop 2 (1 then 2). With toggle set to T, and yellow LED on, Output is muted for tuning. With toggle set to T, and blue and yellow LEDs on, 2 Send is muted for tuning. Sends are grounded when bypassed to eliminate potential noise. Set tuner mute toggle switch to T for tuner mute, set toggle to 1 for loop 1 operation. Optional AC adapter is for LED use only. The Dual Loop operates otherwise without LEDs. All SmolскиTech pedals accommodate right angle plugs and are hand wired for True bypass.

SPECIFICATIONS



Controls.....	Foot switch (Loop 1 or Tuner on/off) Foot switch (Loop 2 on/off) Toggle switch (Tuner mute on/off)
Indicators.....	Blue LED (indicates Loop 2 on) Yellow LED (indicates Loop 1 or Tuner on)
Connectors.....	Input Output 1 or T Send 1 Return 2 Send 2 Return
Power Supply.....	AC adapter (use Boss-style center pin negative {-} 9V DC: Optional)
Dimensions.....	4.39(W) x 2.34(D) x 1.19(H) inches (foot switches add about 5/8" to H)
Weight.....	about 11 oz
Accessories.....	Owner's Manual Rubber feet (4): Optional

www.smolskitech.com

© 2010 SmolскиTech

