



Owner's Manual

INPUT - connect to guitar or effect before loop or loop before loop

OUTPUT - connect to amp or another loop

1 SEND - connect to first pedal (in Loop 1) input, or tuner input

1 RETURN - connect to last pedal (in Loop 1) output

2 SEND - connect to first pedal (in Loop 2) input, or tuner input

2 RETURN - connect to last pedal (in Loop 2) output

* Use the SmolскиTech Dual Loop anywhere to eliminate loading down of signal. For use where you experience loss of tone and/or volume while pedals are bypassed (or off). Loop 1 is wired in series with loop 2 (1 then 2). Sends are grounded when bypassed to eliminate potential noise. With a tuner connected to 1 or 2 Send only, output is grounded for silent tuning. Optional AC adapter is for LED use only. The Dual Loop operates otherwise without LEDs. All SmolскиTech pedals accommodate right angle plugs and are hand wired for True bypass.

SPECIFICATIONS



Controls.....	Foot switch (Loop 1 or tuner on/off) Foot switch (Loop 2 or tuner on/off)
Indicators.....	Blue LED (indicates Loop 1 or tuner on) Yellow LED (indicates Loop 2 or tuner on)
Connectors.....	Input Output 1 Send 1 Return 2 Send 2 Return
Power Supply.....	AC adapter (use Boss-style center pin negative {-} 9V DC: Optional)
Dimensions.....	4.39(W) x 2.34(D) x 1.19(H) inches (foot switches add about 5/8" to H)
Weight.....	about 9 oz
Accessories.....	Owner's Manual Rubber feet (4): Optional

www.smolskitech.com

© 2011 SmolскиTech

